

Comparison of cryogenic radiometry and thermal radiometry calibrations at NIST using multichannel filter radiometers

B Carol Johnson¹, Steven W Brown¹, Keith R Lykke¹,
Charles E Gibson¹, Giulietta Fargion², Gerhard Meister²,
Stanford B Hooker³, Brian Markham⁴ and James J Butler⁵

¹ Optical Technology Division, National Institute of Standards and Technology, 100 Bureau Drive, MS 8441, Gaithersburg, MD 20899-8441, USA

² SIMBIOS Project, Code 970.2, NASA Goddard Space Flight Center, Greenbelt, MD 20771, USA

³ Laboratory for Hydrospheric Processes, Code 970.2, NASA Goddard Space Flight Center, Greenbelt, MD 20771, USA

⁴ Landsat Project Science Office, Code 923, NASA Goddard Space Flight Center, Greenbelt, MD 20771, USA

⁵ EOS Project Science Office, Code 925, NASA Goddard Space Flight Center, Greenbelt, MD 20771, USA

E-mail: cjohnson@nist.gov

Published 7 February 2003

Online at stacks.iop.org/Met/40/S216

Abstract

Comparison of independent measurement results allows an assessment of the accuracy of the underlying methods. In this work, four multichannel filter radiometers were calibrated using tunable laser-illuminated and lamp-illuminated integrating sphere sources (ISSs). The determination of the radiance of the laser-illuminated ISS is based on electrical substitution radiometry at cryogenic temperatures and dimensional metrology of circular apertures. The determination of the spectral radiance of the lamp-illuminated ISS is based on blackbody physics, referenced to the freezing temperature of gold. By calibrating the filter radiometers using both methods, we compare the ‘detector-based’ to the ‘source-based’ radiance scale at the National Institute of Standards and Technology (NIST).

1. Introduction

Realization of radiometric quantities using new methods based on electrical substitution radiometry and dimensional metrology has resulted in reduced uncertainties compared to methods based on temperature scales and blackbody physics. The methods are referred to as ‘detector-based’ and ‘source-based’ radiometry, respectively, reflecting the different transfer standards used. At the National Institute of Standards and Technology (NIST), the spectral radiance values assigned to lamp-illuminated integrating sphere sources (ISSs) are determined by reference to a gold-point blackbody. Such lamp-illuminated ISSs are often used to calibrate radiometers. A detector-based method of calibrating a radiometer that incorporates a laser-illuminated ISS is also possible at NIST,

resulting is the absolute radiance (or irradiance) responsivity at an arbitrary number of discrete wavelengths within the instrument’s bandpass.

When a filter radiometer, calibrated using the detector-based method, is used to measure broadband sources such as lamp-illuminated integrating spheres, the radiance responsivity, multiplied by the source spectral radiance and integrated over wavelength, predicts the signal that should be observed. We used four multichannel filter radiometers designed for radiance measurements and a large-area lamp-illuminated source to compare the two techniques. Use of narrow field-of-view filter radiometers, calibrated using the more accurate laser technique, to determine the temperature of a small-aperture, high-emittance variable-temperature blackbody is a method to generate a detector-based spectral

radiance scale. Hence this work also gave us experience in the steps required to implement a detector-based spectral radiance scale at NIST, similar to that accomplished recently in spectral irradiance [1].

2. Instrument and facility descriptions

Here we describe the relevant properties of the filter radiometers and the two methods used to calibrate them. The multichannel filter radiometers are used to validate the spectral radiance values assigned to large-area ISSs, such as those used to calibrate satellite sensors in the Earth Observing System (EOS) prior to launch [2]. The optical design of each radiometer is similar, with six independent channels, a commercial camera objective lens and an electronic interface for data acquisition. The filters and detectors are temperature stabilized. At a 1 m working distance, the target diameter is about 50 mm.

The SeaWiFS Transfer Radiometer (SXR) [3] was built to support calibration efforts in an ocean colour satellite program, the Sea-viewing Wide Field-of-view Sensor (SeaWiFS). The Visible Transfer Radiometer (VXR) [4] is used in EOS calibration intercomparisons. The LandSat Transfer Radiometer (LXR) [5] is part of the Enhanced Thematic Mapper Plus (ETM+) calibration program. The SXR-II is used for source comparisons [6] in the Sensor Intercomparison and Merger for Biological and Interdisciplinary Ocean Studies (SIMBIOS) program.

The centre wavelengths (between 412 nm and 870 nm) and bandwidths (~ 10 nm) in the SXR, VXR and SXR-II correspond to a subset of those used for ocean science products. Likewise in the LXR, four channels correspond to a subset of the ETM+ channels; they are broadband (60 nm to 100 nm) with centre wavelengths of 481 nm, 560 nm, 661 nm and 821 nm. The interference filters in the remaining two LXR channels have the same design specifications as the 441 nm and 662 nm filters in the other three radiometers. Aside from the difference in the bandwidths, the pre-amp gains in the SXR and SXR-II were chosen for lower level sources than for the VXR and LXR. Consequently, the SXR and SXR-II saturate before the VXR and LXR.

The Spectral Irradiance and Radiance Responsivity Calibrations with Uniform Sources (SIRCUS) facility [7] was used to determine the absolute radiance responsivity at many wavelengths in both the in-band and out-of-band region of each channel for all four filter radiometers. In SIRCUS, the radiometers viewed a laser-illuminated ISS that provided a known source of monochromatic radiance. The laser-illuminated ISS method offers several advantages, including spectral purity, wavelength accuracy and high radiance levels, over the lamp-illuminated ISS method, resulting in reduced uncertainties [4]. The radiance was determined using a trap detector that was calibrated using a cryogenic radiometer and measurements of the relevant aperture areas and distance. A wide variety of tunable lasers provided coverage from 380 nm to 920 nm.

The NIST Facility for Automated Spectroradiometric Calibrations (FASCAL) [8] was used to calibrate a lamp-illuminated ISS for spectral radiance from 300 nm to 1100 nm by comparison with a variable temperature blackbody. A prism-grating spectroradiometer with reflective foreoptics,

a $0.6 \text{ mm} \times 0.8 \text{ mm}$ target area, and a wavelength-dependent dispersion (maximum value of 3.7 nm mm^{-1} at 800 nm) is used to transfer the spectral radiance of a variable temperature blackbody to the ISS. The temperature of the blackbody is determined by reference to a ribbon filament lamp, which is referenced to a gold-point blackbody. The lamp-illuminated ISS we calibrated was the EOS/NIST portable radiance source (NPR) [9], a 30 cm diameter, internally illuminated, Spectralon⁶ sphere. Up to four lamps can be operated and the signals from two monitor photodiodes are recorded automatically.

3. Results

The measurements are described in table 1. Two sets of SIRCUS studies were performed, in December 2000 and in December 2001. In November 2000, the LXR, SXR and SXR-II measured the NPR on two separate days and were then calibrated on SIRCUS. For the December 2001 measurement set, the SXR-II and the VXR measured the NPR before and after the SIRCUS calibration, with multiple measurements of the individual radiance levels. FASCAL was used to calibrate the NPR in August 2000 and December 2001. The NPR four-lamp level saturates two of the channels in the SXR and the SXR-II, so measurements were not made for that configuration.

The SIRCUS calibration results are sets of radiance responsivity values $R(\lambda)$ at the laser wavelengths used, with each set corresponding to one channel of one of the filter radiometers. For the in-band regions, the wavelength step was about 0.5 nm. Measurements from 380 nm or 400 nm to 930 nm with an interval of 5 nm to 10 nm determined the radiance response in the out-of-band region. The results were interpolated with a resolution of 0.2 nm using a cubic spline routine within the in-band region and linear interpolation for the out-of-band region. For the ETM+ channels in the LXR, linear interpolation was used for the in-band region.

The spectral radiance of the NPR, $L_{\text{NPR}}(\lambda)$, was measured over a broad spectral range, from 300 nm to 1000 nm or 1100 nm, every 25 nm. The values were interpolated onto the same wavelength grid as the $R(\lambda)$ values using a cubic spline routine. Then the predicted signal, S_{P} , was calculated using

$$S_{\text{P}} = \int R(\lambda) L_{\text{NPR}}(\lambda) d\lambda \quad (1)$$

and compared to the net measured signal, S_{M} . This process was repeated for every separate measurement of the different radiance levels for each of the 30 channels among the four filter radiometers (including the two separate SIRCUS calibrations of the SXR-II).

4. Summary

Four multichannel filter radiometers were used to compare the detector-based scale from SIRCUS to the source-based scale from FASCAL using the NPR as a transfer source. The results agree within the combined expanded uncertainties, thus validating the accuracy of both the NIST detector-based and source-based methods. Work is in progress using filter radiometers with very narrow fields-of-view so that the blackbody standards can be addressed directly.